

Datasheet

- **V23-1201 12V 100mA Power Supply 114654**

- V23-1201 12V 100mA Universal Power Supply supplied with Vision Gold masthead kits
- Ideal power supplies for Vision Gold range of amplifiers and other standard 12V masthead amplifiers
- Full short-circuit & overload protection with red/green LED indicator for overload and safe operation
- Internal temperature sensing for improved safety
- Fully screened RF loop-through with F-Connectors for lower insertion loss
- Fully screened variable attenuator on V23-1201 for convenient and easier set-up
- 0.6m mains lead with UK mains plug with 3A fuse fitted
- Visible fixing lugs and screw holes for easy fixing



Model	V23-1201 114654
Outage Voltage	12V-negative earth. Centre pin +ve
Current	100mA
DC Short-circuit / overload protection	12V regulated output with s/c protection. Red LED indicates overload or short circuit. Green LED indicates power on.
Frequency range	5 to 862MHz
Insertion Loss	<0.5dB
RF Connections	F-female for input and output
Loop-through	Diecast fully screened with integral F-female connectors DC pass to input – DC blocked to output
Mains voltage	230V AC ±10% 50Hz
Mains voltage protection & safety	3A mains fuse in UK standard plug. Positive Temperature Coefficient (PTC) transformer temperature sensing device
Mains Plug	UK standard moulded plug with 3A fuse to BS1363
Lead	0.6m 2-core mains lead
Operating Temperature	-5°C ~ +50°C
Size	106mm x 51mm x 38mm including fixing lugs
Weight Kg	0.35
Packing	Individual carton. 50 per outer
RoHS Compliance	RoHS Compliant. Exempt from WEEE/RoHS directive as at 15/03/07. Intended for professional use as part of a fixed installation only